

## DS-K1102A Pro 1102A Series Card Reader



- Built-in audible beeper
- RS-485 and Wiegand (W26/ W34) protocol
- Tamper-proof alarm
- Supports reading EM card (Frequency: 125 KHz) (DS-K1102AE/DS-K1102AEK/DS-1102AEM)
- Supports reading M1 card (Frequency: 13.56 MHz). (DS-K1102AM/DS-K1102AMK/DS-K1102AEMK)

## ▪ Specification

Interface	
RS-485	1 RS-485. Supports OSDP protocol, Baud 9600, 19200, 38400
Authentication	
Card reading frequency	DS-K1102AE/DS-K1102AEK/DS-K1102AEM/DS-K1102AEMK: 125 KHz DS-K1102AM/DS-K1102AMK/DS-K1102AEM/DS-K1102AEMK: 13.56 MHz
General	
Power supply	12 VDC, 500 mA
Power consumption	≤ 2 W
Working temperature	-20 °C to 65 °C (-4 °F to 149 °F)
Working humidity	10% to 90% (no condensing)
Dimensions	121 mm × 86.5 mm × 14 mm (4.76" × 3.41" × 0.55")
Installation	Applied for 86 & 120 gang box
Weight	≤ 0.14 kg (0.3 lb)
Keypad	DS-K1102AE/DS-K1102AM/DS-K1102AEM: No Keypad DS-K1102AEK/DS-K1102AMK/DS-K1102AEMK: Keypad with 12 keys (0 to 9, *, #)
Buzzer	Beeper
Function	
ID settings	via DIP switch

## ▪ Available Model

DS-K1102AE  
 DS-K1102AEK  
 DS-K1102AEM  
 DS-K1102AEMK  
 DS-K1102AM  
 DS-K1102AMK  
 DS-K1102AMK/HIKVISION USA INC.  
 DS-K1102AM/HIK USA  
 DS-K1102AMK/Part  
 DS-K1102AMK/HIK USA  
 DS-K1102AM/ACT-R2102M/HW  
 DS-K1102AM/USA INC  
 DS-K1102AM/HIKVISION USA INC.

## ▪ Accessory

### ▪ Included



### ▪ Optional

**DS-K3G200LX**



# See Far, Go Further



[www.hikvision.com](http://www.hikvision.com)  
[support@hikvision.com](mailto:support@hikvision.com)

